



# SIGNAL

Xignal is a brand of Dimo Systems • The Netherlands

## Specifications Rat trap



### Detect

Xignal detects the status of the mouse and rat traps 24/7. Armed, closed with or without catch.



### Send

Through LoRa technology, sensors communicate via your public or private network. LoRa can cover up to 150,000 ft<sup>2</sup>. From sensors to portal, Xignal is your easy to use solution.



### Report

By a notification to your phone, tablet, laptop, or PC, you receive timely pest activity reports. Take immediate action when notified of captures.

Download the Xignal app or go to  
[my.xignal.com](https://my.xignal.com)





# Rattrap product specifications

## TECHNICAL SPECIFICATION

MODEL  
PACKET DATA  
RADIO FREQUENCY  
BATTERY  
UI  
LABEL

## XIGNAL RATTRAP

V1.5  
Uses LoRa ADR  
EU 868 Mhz / US 915 Mhz  
CP502440 Li-MnO2 battery  
RGB LED and 2 switches  
QR code and unique serial number

## PHYSICAL DESCRIPTION

PRODUCT DIMENSIONS  
WEIGHT  
CHASSIS MATERIAL

L: 138.9 mm x W: 75.8 mm x H: 67 mm  
197 g (6.948 oz) with PCB antenna and battery installed  
ABS plastic

## ENVIRONMENTAL

OPERATING TEMPERATURE  
RELATIVE HUMIDITY  
INGRESS PROTECTION (IP) RATING

-10°C to 55°C (14°F to 131°F)  
0% to 95%  
IP67: complete protection against contact and immersion in water, up to 30 minutes in 1m (3 ft 3 in) depth (max. 1/2 half hour)

## CERTIFICATIONS

EMC COMPLIANCE  
  
RADIO COMPLIANCE  
  
ROHS COMPLIANCE  
REACH COMPLIANCE  
WEEE COMPLIANCE

EN 61000-6:2001 & EN 61000-6-3:2001 & EN 55032:2015  
LoRa Alliance certified by certification by similarity of the embedded RN2483A  
Directive 2002/95/EC & 2011/65/EU  
Regulation 1907/2006 including amendments  
Directive 2012/19/EU



Xignal is a brand of Dimo Systems  
Rondgang 10 • 5311 PB Gameren • The Netherlands

[www.dimosystems.com](http://www.dimosystems.com)